

AC300

Expandable Power At Your Will

Power For Long, Blackout Worries Gone



All Your Need in One



App Control



Fast Charge



LiFePO₄ Battery



BMS



12V/30A DC Output



24V Car Outlet



24/7 UPS



TT-30 AC Outlet



US / JP



EU



UK



AU



SA



CN

24/7 UPS (uninterruptible power supply)

No need for complicated installation; simply place it anywhere in your house or garage. When a power outage occurs, the AC300 automatically kicks in and provides emergency power to your appliances in just 20ms.



AC300+B300

Specs

Model:	AC300+B300
Capacity:	3072Wh~12288Wh (1~4*B300)
Battery:	LiFePO ₄ , 3,500+ life cycle
Output Power:	3,000W (6,000W surge) 6000W(Split Phase Bonding for 100/120V Model only)
Weight:	57kg/125.7lbs (AC300+1*B300)
UPS:	Switching times 20ms
App Control:	WiFi & Bluetooth
Dimensions (Lx WxH)	52.0X32.5X35.8cm/20.5x12.5x14.in
Operating Temperature	32°F ~ 104°F/0°C ~40°C
Storage Temperature	-4°F~-104°F/-20°C ~40°C

Shenzhen Poweroak Newener Co., Ltd.

Add: 19F, Block A, Kaidaer Bldg., No.168 Tongsha Rd., Nanshan Dist., Shenzhen, Guangdong, China
 FAX: feedback@bluetti.com
 TEL: 0752-5192099

BLUETTI ENERGY NETHERLANDS

Add: Kabelweg 57, Amsterdam, The Netherlands
 FAX: sales_nl@bluetti.com

Poweroak GmbH

Add: Lise-Meitner-Straße 14, 28816 Stuhr, Germany
 FAX: sale-de@bluettipower.com
 TEL: +49 151 10622908

BLUETTI ENERGY FRANCE SARL

Add: 72 boulevard Edgar Quinet 75014 Paris
 FAX: sales.fr@bluetti.com
 TEL: +33 0784711486

BLUETTI ENERGY ITALY SRL

Add: GALLERIA DEL CORSO 1, 20122, Milano, Italy
 FAX: james@bluetti.com
 TEL: +39 324 286 5555

BLUETTI ENERGY SPAIN S.L

Add: calle alajate 3 2B Madrid Spain 28041
 FAX: es@bluetti.com
 TEL: 666189625

Customizable Power Solution

Experience true customization with the AC300. Its modular design allows you to tailor your power capacity to your exact needs. Just hook up to four *B300 expansion batteries, and unlock a whopping capacity of 12,288Wh. With this generous supply, you can confidently energize your entire home or be ready for any sudden outages.

AC300+B300 (X1) AC300 B300x1: 3072Wh	AC300+B300 (X2) AC300 B300x2: 6144Wh	AC300+B300 (X3) AC300 B300x3: 9216Wh	AC300+B300 (X4) AC300 B300x4: 12288Wh AC300X2 B300X2-8 6000W/6144Wh~24,576Wh
3,072Wh	6,144Wh	9,216Wh	12,288Wh

Split Phase Bonding is available for 120V, Compatible with 2-8 *B300

Input

AC Input:	3000W Max
Solar Charging:	24000W Max Dual MPPT
Car Charging:	12/24V 8A
Solar + AC Charging:	5400W Max

Output

Cigarette Lighter Port x1:	24V/10A
RV Portx1:	12V/30A
USB-Ax2:	12V/30A
USB-A (QC3.0) x2:	5V/3A, 15W Max.
USB-Cx1:	5V ~12V/3A, 18W Max.
For 100/120V Model	
AC Outlet x6:	25A 100V / 50HZ(UP) 30A 120V / 60Hz (US)
30A AC Outletx1:	TT-30, 120V
For 220V~240V Model	
AC Outlet x6:	13A 230V / 50HZ
Wireless Charging Pad x2:	5/7.5/10/15W